
POLE P454-CC



DESCRIPTION

The pole shall consist of a base and a shaft. The cast aluminum base shall be round in shape. The castings shall be of uniform wall thickness with no warping or mold shifting and shall be formed true to the original pattern with complete detail. The tapered shaft shall be made of cast aluminum with 10 flutes and shall be circumferentially welded over and in the base. A cast aluminum donut shall cover the weld. The donut shall be fastened with stainless steel hardware. A 4" x 6" x 7"H service door shall be located at 17" to center from the bottom of pole.

DIMENSIONS

The pole shall be 11'-2" in height. The base shall be 20" in diameter.

MOUNTING

The pole shall be supplied with a sturdy steel template and with 4 hot dipped galvanized 3/4" x 24" long "L" type anchor bolts with two nuts and two washers each. These will install on an 11-1/2" bolt circle with anchor bolts extending 3" above the ground level. An optional 3"H x 4"OD tenon is available for fixture mounting. Custom tenon sizes may be available.

FINISH

All applicable parts shall receive a standard electrostatically applied thermoset polyester powder coat smooth semi gloss finish with a four part corrosion inhibiting process.


CONTACT INFORMATION




(800) 267-3175 (905) 238-2648 1280 Fewster Drive Mississauga Ontario L4W 1A4 Canada Fax (905) 238-9060 Email sales@hcilighting.com WEB www.hcilighting.com

COLOR AND OPTIONS

There are five standard RAL colors to choose from: Black 9011, Green 6005, Bronze 8019, Grey 7012 and White 9016. Custom colors are available for an upcharge. A variety of options is available. For more information please see the *Finishes* and *Options* sections.





EPA INFORMATION

Model	Height	Wall thickness (in)	Diameter (in)	EPA rating			
number	(ft)			80 mph (sa.ft)	90 mph (sq.ft)	100 mph (sq.ft)	
				(54.11)	(54.11)	(54.11)	
P454-CC	11.2	0.375	6 5/8 - 4	35.64	28.51	23.21	

HCI, Ltd. neither designs nor recommends concrete footing size

OPTIONS

SRT single receptacle			
DRT double receptacle			
GFI GFI receptacle			
BA1-BM single bolt-on 24"L banner arm			
BA1-CM single clamp-on 24"L banner arm			
BA1H-BM single bolt-on 24"L banner arm with hog ring			
BA1H-CM single clamp-on 24"L banner arm with hog ring			
BA1-BBM single bolt-on break-away 24"L banner arm			
BA1H-BBM single bolt-on break-away 24"L banner arm			

with hog ring

street sign

SS1-CM single clamp-on

Ordering Sequence Example:

Luminaire	Fitter	Diffuser	Light Source	Voltage	Optical System	Arm	Configuration	Pole	Finish	Options
F100-L	B4	FPC	150HPS	120V	LV-L5	A307	2A	P454-CC	RAL9011	SRT